

PRODUCT NUMBER: 1013461 Leightning L0F folding earmuff

Learn more about our products at howardleight.com

Honeywell HOWARD LEIGHT

Overview

Reference Number

1013461

Product Type

Hearing Protection

Range

Earmuffs

Line

Noise Blocking Earmuffs

Branc

Howard Leight by Honeywell

Brand formerly known as

BILSOM

Industry

- Industry Administration Agriculture Army Defence Automotive and Part Manufacturer
- Fire Protection brigades Fishing Food Industries Foundry Glass Industries Green Space
- Homeland defense Industrial Cleaning Iron and steel industry Laboratory Logistics
- Maintenance Medical and Pharmaceutical Metal steel Minning and Quarrying Offshore
- Paper Industries
 Petro-chemical
 Printing Industries
 Services
 Ship Building
 Telecoms
- Textile Industries Transportation Utilities Water treatment Welding Wood Industries

Product Use

Convenient folding headband design for easy storage

Features & Benefits

Feature

AIR FLOW CONTROL TECHNOLOGY Bilsom's patented Air Flow Control™ technology delivers optimal attenuation across all frequencies, without increasing earcup size or weight. A patented baseplate chamber and high-tech non-woven layer manage the flow of air inside the earmuff to control how sound reaches the ear. The result is better, more consistent overall attenuation for virtually all industrial noise environments. STEEL WIRE CONSTRUCTION Robust steel headband withstands demanding use, especially in tough environments. ULTRASLIM EARCUPS Ideal for low noise levels. SNAP-IN

Leightning LOF folding earmuff - 1013461

EAR CUSHIONS Snap-in ear cushions make replacement quick and easy. PADDED FOAM HEADBAND Delivers long-wearing comfort with minimal pressure on the head.

Benefit

When you're in a tough industrial environment and need to block noise, Bilsom's Leightning series' steel wire construction provides high performance and robust durability. Leightning stands up to daily use and abuse without compromising comfort. Bilsom has optimized the Leightning series to deliver the highest level of comfort available, featuring an exclusive padded foam headband and super soft ear cushions that eliminate that "squeezing pressure" on the head.

Technical Description

SNR (dB)

25

H (dB)

27

M (dB)

21

L (dB)

17

Attenuation Data

Frequency (Hz) Frequenz (Hz) Fréquence (Hz)631252505001000200040008000Mean Attenuation (dB) Mittlere Dämmung (dB) Atténuation moyenne (dB)13.219.721.725.029.135.137.940.0Standard Deviation (dB) Standardabweichung (dB) Déviation standard (dB)3.03.72.83.52.52.33.42.6Assumed Protection (dB) Angenommener (dB) Protection supposée (dB)10.216.118.921.526.632.834.637.4

Earmuff Construction

Metal

Other Material

Steel Wire, PUR-E, PVC, Textile, PC/PBT, ABS

Dielectric

No

Color

Black

Batteries Needed

None

Weight (grs)

172

Design Patents

Air Flow Control

Headband Style

Folding

Sound Amplification

No

AM/FM Radio

No

Automatic Shut-Off Function

No

Audio Input Jack

No

Hi-Visibility

No

Certifications

EC Category PPE

2

Quality Assurance

ISO 9001 / 2000

EC Certificate Number

EC1458

EC Attestation

EC Attestation

EC Attestation Number

060205

Literature & Documents

PIC SKU - Pictures

http://www.honeywellsafety.com/assets/0/324/500/51887/aebe6291e6934edf8e4d1dbea92de9e0.jpg

Maintenance

Life Cycle

Cushions should be replaced periodically to retain maximum attenuation. Use the following as a guideline for replacement of ear cushions and insert foam. General use and wear - Ear cushions and foam inserts should be replaced at least every 6 months. Heavy use or wear in humid/extreme climates - Ear cushions and foam inserts should be replaced at least every 3 months. Cracking or leakage is visible - replace ear cushions and foam inserts immediately.

Storage Information

When not in use, the earmuffs should be stored in a clean dry container or locker. Do not use solvents or petroleum-based products. Do not immerse the earmuffs in water.

Care Instructions

Earmuffs are an important safety product and should be inspected regularly. Its use, care and maintenance are critical to its effective performance. Earmuffs and in particular ear cushions may deteriorate with use and should be examined at frequent intervals for cracking and leakage. If the ear cushions become hard, damaged or deteriorated, they should be replaced promptly using recommended Hygiene Kits. Earmuffs should be maintained by regular cleaning. Use a mild disinfectant solution. A gentle wipe is all that is required.

Parts & Accessories

Accessories

Hygiene Kit - Packed in a plastic bag, including two ear cushions and two liners. Ref. # 1011998 for L1N, L1H, L1N, L0N, L0F

Belt case - For carrying purpose. Ref. # 1000251

Cool II Pads - Sweat absorbing pads. Ref. # 1000365 5-pair, Ref. # 1000364 100-pair

Optisorb - cotton sleeve slides over earcup. Ref. # 3302101

Polar Hood - Ref. # 1016870 Lg/XLg; Ref. # 1016871 Sm/Med

Packaging

EAN Code

7312550134610

© Honeywell International Inc.